

LAMPES AMERICAINES I

TYPE	MESURE	SOCLE	SELECTEUR							FILAM	GRILLE	PLAQUE	ECRAN.I	ECRAN.II	CATH	VIDE	DEBIT
			I	II	III	IV	V	VI	VII								
01A		J	5	2	0	0	0	0	0	B	A	5	9	135			3.
00A		J	5	2	0	0	0	0	0	B	A	5	0	45			1.5
1	PL 1	J	6	0	0	0	0	0	0	B	A	6.3		250			50.
	PL 2	J	0	6	0	0	0	0	0	B	A			250			50.
1A4		J	5	3	0	0	0	0	2	B	A	2.	3	180	67.5		2.3
1A5		J	5	3	2	0	0	0	0	B	A	1.4	4.5	90	90		4.
1A6	Ampl- Oscill-	L	5	0	0	3	0	0	0	B	A	2	3	180	67.5	135	1.3
		O	0	5	2	0	0	0	0	B	A	2	3	135			0.4
1A7	Ampl-	O	5	3	0	0	0	0	0	B	A	1.4	0	90	45		0.55
		L	0	0	2	5	0	0	0	B	A		0	90			0.4
1B4		J	5	3	0	0	0	0	2	B	A	2	3	180			1.7
1B5	Triode Diode 1	L	5	0	0	2	0	0	0	B	A	2	3	135			0.8
		O	0	0	8	0	0	0	0	B	A						1.
1C5	Diode 2	O	0	0	8	0	0	0	0	B	A						1.
		L	0	0	0	8	0	0	0	B	A						1.
1C6	Ampl- Oscill-	O	5	3	2	0	0	0	0	B	A	1.4	7.5	90			7.5
1C7	Ampl- Oscill-	L	5	0	0	3	0	0	2	B	A	2	3	180	67.5		1.5
		O	0	5	2	0	0	0	0	B	A	2	3	180	67.5		0.4
1D7	Ampl- Oscill-	O	5	3	0	0	0	0	2	B	A	2	3	180	67.5		1.5
		L	0	0	2	5	0	0	0	B	A		3	135			0.4
1E4		O	5	0	2	0	0	0	0	B	A	1.4	3	90			1.5
1E5		O	5	3	0	0	0	0	2	B	A	2.	3	180	67.5		1.7
1E7	Penth	O	5	2	0	0	3	0	0	B	A	2.	7.5	135	135		6.5
1F4		K	5	2	3	0	0	0	0	B	A	2.	4.5	135	135		8.
1F5		O	5	3	2	0	0	0	0	B	A	2.	4.5	135	135		8.
1F6	Penth Diode 1	L	5	3	0	0	0	0	2	B	A	2.	1.5	180	67.5		2.2
		O	0	0	0	8	0	0	0	B	A	2.		250			1.
1F7	Penth Diode 1	O	0	0	0	8	0	0	0	B	A	2.		250			1.
		L	0	0	0	8	0	0	0	B	A	2.		250			1.
1G4	Diode 2	O	0	0	8	0	0	0	0	B	A	2.		250			1.
		L	0	5	0	2	0	0	0	0	B	A	1.4	6	90		
1G5		O	5	3	2	0	0	0	0	B	A	2.	6	90			8.5
1G6	Triode 1 Triode 2	O	5	2	0	0	0	0	0	B	A	1.4	0	90			1.
		L	0	0	0	2	5	0	0	0	B	A	1.4	0	90		
1H4		O	5	0	2	0	0	0	0	B	A	2.	9	135			3.
1H5	Triode	O	5	0	0	0	0	0	2	B	A	1.5	0	90			0.15
1H6	Triode Diode 1	O	0	0	8	0	0	0	0	B	A						1.
		L	0	5	0	2	0	0	0	0	B	A	2.	3	135		
1J5	Diode 2	O	0	0	8	0	0	0	0	B	A						1.
		L	0	0	8	0	0	0	0	B	A						1.
1J6	Triode	O	5	3	2	0	0	0	0	B	A	2.	16.5	135	135		7.
		L	0	5	2	0	0	0	0	0	B	A	2.	0	135		
1N5		O	0	0	2	5	0	0	0	B	A		0	135			27.
1P5		O	5	3	0	0	0	0	2	B	A	1.4	0	90			1.2
1V		O	5	3	0	0	0	0	2	B	A	1.4	4.5	90	90		9.5
2A3		J	6	1	0	0	0	0	0	B	A	6.3		250			50.
2A5		J	5	2	0	0	0	0	0	B	A	2.5	45	250			60.
2A5		L	5	3	2	1	0	0	0	B	A	2.5	16.5	250	250		34.

TYPE	MESURE	Wedge	SELECTEUR												Filam	Grilles	Plaques	Ecran 1	Ecran 2	Cathode V. de	Debit
			I	II	III	IV	V	VI	VII	VIII	IX	X	XI	XII							
2A6	Triode Diode 1 Diode 2	L	5	0	0	-1	0	0	2	B	A	2.5	2	250						0.9	
			0	0	0	1	0	0	0	B	A			250						1.	
2A7	Ampl Oscill.	M	5	3	-1	-1	-1	0	2	B	A	2.5	3	250	100					7.5	
			0	0	5	2	1	0	0	B	A		0	250						1.4	
2B6		M										2.5	24	250						40.	
2B7	Penlt- Diode 1 Diode 2	M	5	3	0	0	-1	0	2	B	A	2.5	3	250	-100					6.	
			0	0	0	8	0	1	0	0	B	A		250						1.	
2D1	Diode 1 Diode 2	K	8	0	-1	0	6	0	0	B	A	2.5		250						1.	
			0	0	1	0	0	0	0	B	A			250						1.	
2W3		O	0	0	6	0	0	B	0	0	0	2.5		250						50.	
5T4	Plaque 1 Plaque 2	O	0	0	6	0	0	B	0	0	0	5.		250						50.	
			0	0	0	0	6	B	0	0	0			250						50.	
5U4	PL 1	O	0	0	6	0	0	B	0	0	0	5.		250						50.	
	PL 2		0	0	0	0	6	B	0	0	0			250						50.	
5V4	PL 1	O	0	0	6	0	0	A	0	0	0	5.		250						50.	
	PL 2		0	0	0	0	6	A	0	0	0			250						50.	
5W4	PL 1	O	0	0	6	0	0	B	0	0	0	5.		250						50.	
	PL 2		0	0	0	0	6	B	0	0	0			250						50.	
5X4	PL 1	O	6	0	0	0	0	A	0	0	0	5.		250						50.	
	PL 2		0	0	0	6	0	A	0	0	0			250						50.	
5Y3	PL 1	O	0	0	6	0	0	B	0	0	0	5.		250						50.	
	PL 2		0	0	0	0	6	B	0	0	0			250						50.	
5Y4	PL 1	O	6	0	0	0	0	A	0	0	0	5.		250						50.	
	PL 2		0	0	6	0	0	A	0	0	0			250						50.	
5Z3	PL 1	J	6	0	0	0	0	0	0	B	A	5.		250						50.	
	PL 2		0	6	0	0	0	0	0	B	A			250						50.	
5Z4	PL 1	O	0	6	0	0	0	A	0	0	0	5.		250						50.	
	PL 2		0	0	0	6	0	A	0	0	0			250						50.	
6A3		J	5	2	0	0	0	0	0	B	A	6.3	45	250						60.	
6A4		K	5	2	3	0	0	0	0	B	A	6.3	42	180	180					22.	
6A5		O	5	0	2	0	0	0	0	B	A	6.3	45	250						60.	
6A6	Triode	M	5	2	1	0	0	0	0	B	A	6.3	5	250						6.	
	Ampl-		0	0	1	2	5	0	0	B	A		5	250						6.	
6A7	Oscill-	M	5	3	-1	-1	-1	0	2	B	A	6.3	3	250	100					7.5	
	Ampl-		0	0	5	2	-1	0	0	B	A		0	250						1.4	
6A8	Oscill.		5	3	-1	-1	-1	1	2	B	A	6.3	45	250	70					4.	
			0	0	2	5	-1	-1	0	B	A		0	250						1.5	
6AB5		L	9	2	3	1	0	0	0	B	A	6.3	7.5	135	135					VISUEL	
6AB7	V. de H803																			50.	
6AC5		O	5	0	2	0	1	0	0	B	A	6.3	0	250						10.	
6AC7		O	1	2	-1	3	5	0	0	B	A	6.3	20	250	200	200				50.	
6AD6		O	0	8	8	3	0	1	0	0	B	A	6.3		75	150				VISUEL	
6AE6		O	0	5	4	2	0	1	0	0	B	A	6.3	4.5	250	250				6.5	
6AF7	Elam-1 Elam-2	O	9	2	3	-1	1	0	0	B	A	6.3	0.5	250	250					VISUEL	
			-1	2	3	9	-1	0	0	B	A		0-19	250	250					VISUEL	
6B4		O	5	0	2	0	1	0	0	B	A	6.3	45	250						60.	
6B5		L	5	3	2	-1	0	0	0	B	A	6.3	0	250	250					45.	
6B6	Triode	O	5	0	0	0	-1	0	2	B	A	6.3	2	250						1.	

TYPE	MESURE	SOLE	SELECTEUR								FILAM	SERIE	FLADUE	ECRAN.I	ECRAN.II	CATH	VIDE	DEBIT
			I	II	III	IV	V	VI	VII	VIII								
6B6	Diode 1		0	0	0	1	0	0	0	B	A	6.3		250				1.
	Diode 2		0	0	0	1	0	0	0	B	A			250				1.
6B7	Pentb-	N	5	3	0	0	1	0	2	B	A	6.3	W	250	125			9.
	Diode 1		0	0	0	0	1	0	0	B	A			250				1.
	Pentb-		0	0	0	0	1	0	0	B	A			250				1.
6B8	Diode 1	O	5	0	0	3	1	0	2	B	A	6.3	3	250	100			6.8
	Diode 1		0	0	0	0	1	0	0	B	A			250				1.
	Diode 2		0	0	0	0	1	0	0	B	A			250				1.
6C5		O	5	0	2	0	1	0	0	B	A	6.3	8	250				8.
6C6		L	5	3	1	1	0	0	2	B	A	6.3	3	250	100			2.
6C7	Triode	M	5	0	0	0	1	0	2	B	A	6.3	9	250				4.5
	Diode 1		0	0	0	0	1	0	0	B	A			250				1.
	Diode 2		0	0	0	0	1	0	0	B	A			250				1.
6C8	Triode 1	O	5	1	0	0	0	0	2	B	A	6.3	4.5	250				3.2
	Triode 2		0	0	2	5	1	0	0	B	A		4.5	250				3.2
6D1	Diode 1	K	0	0	1	0	0	0	0	B	A	6.3		250				1.
	Diode 2		0	0	1	0	0	0	0	B	A			250				1.
6D5		L	5	0	2	0	1	0	0	B	A	6.3	40	250				28.
6D6		L	5	3	1	1	0	0	2	B	A	6.3	3	250	100			8.2
6D7		M	5	3	1	1	0	0	2	B	A	6.3	3	250	100			2.
6D8	Ampl-Oscill-	O	5	3	1	1	1	0	2	B	A	6.3	5	250	100			3.
			0	0	2	5	1	0	0	B	A		0	250				0.8
6E5		L	2	2	3	1	0	0	0	B	A	6.3	0-8	250	250			VISUEL
6E6	Triode 1	M	5	2	1	0	0	0	0	B	A	6.3	27.5	250				18.
	Triode 2		0	0	1	2	5	0	0	B	A		27.5	250				18.
6E7			5	3	1	0	1	0	2	B	A	6.3	3	250	100			8.2
6E8	Ampl-Oscill-	O	5	3	1	1	1	1	2	B	A	6.3	5	250	100			2.3
			0	0	2	5	1	0	0	B	A		5	100				1.
6F5		O	0	5	0	0	1	0	2	B	A	6.3	2	250				1
6F6		O	5	3	2	0	1	0	0	B	A	6.3	16.5	250	250			34.
6F7	Pentb-		5	3	0	0	1	0	2	B	A	6.3	3	250	100			6.5
	Triode 1		0	0	0	5	2	1	0	B	A		3	100				3.5
6F8	Triode 2	O	5	1	0	0	0	0	2	B	A	6.3	8	250				9.
			0	0	2	5	1	0	0	B	A		8	250				9.
6G5		L	9	2	3	1	0	0	0	B	A	6.3	0-20	250	250			VISUEL
6G6		O	5	3	2	0	1	0	0	B	A	6.3	9	100	100			15.
6H6	Diode 1	O	8	1	0	0	0	0	0	B	A	6.3		250				1.
	Diode 2		0	0	0	0	1	0	0	B	A			250				1.
6J5		O	5	0	2	0	1	0	0	B	A	6.3	8	250				9.
6J7		O	5	3	1	0	1	0	2	B	A	6.3	3	250	100			2.
6J8	Ampl-Oscill-	O	5	3	1	1	1	0	2	B	A	6.3	3	250	100			5.5
			0	0	2	5	1	0	0	B	A		3	100				2.
6K5		O	5	0	0	0	1	0	2	B	A	6.3	3	250				1.1
6K6		O	5	3	2	0	1	0	0	B	A	6.3	16.5	250	250			34.
6K7		O	5	3	1	0	1	1	2	B	A	6.3	3	250	100			7.
6K8	Ampl-Oscill-	O	5	3	1	1	1	0	2	B	A	6.3	3	250	100			2.5
			0	0	2	5	1	0	0	B	A		3	250				0.4
6L5		O	5	0	2	0	1	0	0	B	A	6.3	9	250				8.
6L6		O	5	3	2	0	1	1	0	B	A	6.3	14	250	250			60.

LAMPES EUROPÉENNES

TYPE	MESURE	SOLE	SELECTEUR									FILAM	GRILLE	PLAQUE	ECRAN I	ECRAN II	CATH VIDE	DEBIT
			I	II	III	IV	V	VI	VII	VIII	IX							
AB1	Diode 1	G	8	1	0	0	0	0	0	B	A	4.		250				1.
	Diode 2	G	0	1	0	0	0	0	8	B	A			250				1.
AF2		G	3	1	2	1	0	0	5	B	A	4.	2	200	100			4.25
AG 495	E 444	G	5	1	2	0	0	0	0	B	A	4.	5	200				4.
AG4-100		G	5	1	2	0	0	0	0	B	A	4.	5	150				5.
AK1	Ampl. Oscill.	D	1	5	3	0	3	0	2	B	A	4.	1.5	250	70			1.8
	Voir AK1		1	0	5	2	0	0	0	B	A		0	100				0.5
M0465																		
AL 495		G	5	1	2	0	0	0	0	B	A	4.	18	250				20
APP495		G	5	1	2	0	0	0	3	B	A	4.	12	260	150			20
APP4120		G	5	1	2	0	3	0	0	B	A	4.	18	300	250			24
AR495		G	5	1	2	0	0	0	1	B	A	4.	1.5	200				4.5
AR4-100	E 438	G	5	1	2	0	0	0	1	B	A	4.	3	200				3.
AR4-101		G	5	1	2	0	0	0	1	B	A	4.	2	200				2.5
AS494	E 442	G	3	1	2	0	1	0	5	B	A	4.	0	200	100			15.
AS495		G	3	1	2	0	1	0	5	B	A	4.	0	200	100			1.
AS4-100	E 442 S	G	3	1	2	0	1	0	5	B	A	4.	6	200	100			4.
AS4-104		G	3	1	2	0	1	0	5	B	A	4.	2	200	100			5.
AS4-105	E 445	G	3	1	2	0	1	0	5	B	A	4.	2	200	100			6.
AS4-120	E 452 T	G	3	1	2	0	0	0	5	B	A	4.	2	200	100			5.
AS4-125	E 455	G	3	1	2	0	0	0	5	B	A	4.	2.5	200	100			3.
CB220	Triode 1	D	2	0	0	5	0	0	0	B	A	2.	3.4	160				14.
	Triode 2		0	5	0	0	2	0	0	B	A		3.4	160				14.
D4-18		G	1	0	1	0	0	0	8	B	A	4.		100				1.
DD4-65	Diode 1	G	8	1	0	0	0	0	0	B	A	4.		250				1.
	Diode 2	G	0	1	0	0	0	0	8	B	A			250				1.
DS4-100	Pentbo-Diode	D	1	0	0	2	3	0	5	B	A	4.	2.5	200	70			3.
E 444			1	8	0	0	0	0	0	B	A			250				1.
DS4-100	Pentbo Diode	G	3	1	2	0	0	0	5	B	A	4.	2.5	200	70			3.
			0	1	0	8	0	0	0	B	A			250				1.
DS4-101	Pentbo Diode	D	1	0	0	2	3	0	5	B	A	4.	2.3	200	40			0.6
			1	8	0	0	0	0	0	B	A			250				1.
DS4-101	Pentbo Diode	G	3	1	2	0	0	0	5	B	A	4.	2.3	200	40			0.6
			0	1	0	8	0	0	0	B	A			250				1.
FH4-105		D	1	5	3	0	0	0	2	B	A	4.	2	200	70			3.
E 463	APP 4130	D	1	5	0	2	3	0	0	B	A	4.	22	250	250			36.
G 405	A 402 N	G	5	0	2	0	0	0	0	B	A	4.	3	150				3.5
G 407	A 403	G	5	0	2	0	0	0	0	B	A	4.	9	150				3.5
G 115		G	5	0	2	0	0	0	0	B	A	1.	6	160				2.
G 615		G	5	0	2	0	0	0	0	B	A	6.3	5	200				6.
G 2018		G	5	1	2	0	0	0	0	B	A	20.	5	200				10.
H 210		G	5	0	2	0	0	0	0	B	A	2.	3	200				2.
HP 2-12		G	5	3	2	0	0	0	3	B	A	2.	2	100	100			2.5
HP 2-15		G	5	3	2	0	0	0	3	B	A	2.	2	100	100			2.5
HP 220		G	5	3	2	0	0	0	3	B	A	2.	1	160	70			2.5
HP 221		G	5	3	2	0	0	0	3	B	A	2.	1	160	70			2.5
HP 1018		D	1	5	0	1	3	0	2	B	A	10.	3	250	100			2.5
HP 1118		D	1	5	0	1	3	0	2	B	A	10.	3	250	100			2.5
HP 2018		G	3	1	2	1	0	0	5	B	A	20.	2	200	100			3.
HP 2-18		G	3	1	2	1	0	0	5	B	A	20.	2	200	100			5.
HP 4-100		G	3	1	2	1	0	0	5	B	A	4.	2	200	100			3.

TYPE	MESURE	SOCIÉTÉ	SELECTEUR										Filam.	Grille	Plaque	Ecran I	Ecran II	Cathode	Vide	DEBIT
			I	II	III	IV	V	VI	VII	VIII	IX									
HP 4-101		G	3	1	2	1	0	0	0	5	B	A	4.	2	200	100				3.5
HP 4-105		G	3	1	2	1	0	0	0	5	B	A	4.	2	200	100				5.
HP 4-106	B h 7	G	3	1	2	1	0	0	0	5	B	A	4.	2	200	100				5.
HP 4-115		G	3	1	2	1	0	0	0	5	B	A	4.	2	200	100				4.3
HR 2-10		G	5	0	2	0	0	0	0	0	B	A	2.	4	200					2.
HR 4-06	B 630-7332	G	5	0	2	0	0	0	0	0	B	A	4.	3	200					1.
HR 4-10		G	5	0	2	0	0	0	0	0	B	A	4.	3	200					1.
HR 6-07		G	5	0	2	0	0	0	0	0	B	A	6.3	2	200					2
L 1-90		G	5	0	2	0	0	0	0	0	B	A	1.1	8	160					10.
L 2-10		G	5	0	2	0	0	0	0	0	B	A	2.	6	200					4.
L 4-14		G	5	0	2	0	0	0	0	0	B	A	4.	8	160					12.
L 4-15		G	5	0	2	0	0	0	0	0	B	A	4.	10	200					8.
L 6-10		G	5	0	2	0	0	0	0	0	B	A	6.3	18	200					12.
LD 2-10		G	5	0	2	0	0	0	0	0	B	A	2.	4.5	160					2.
LD 4-08	A 415	G	5	0	2	0	0	0	0	0	B	A	4.	6	200					4.
LD 4-10	A 425	G	5	0	2	0	0	0	0	0	B	A	4.	6	200					4.
LG 2-10		G	5	0	2	0	0	0	0	0	B	A	2.	8	160					5.
LG 6-07		G	5	0	2	0	0	0	0	0	B	A	2.	8	160					5.
LP 2-20		G	5	0	2	0	0	0	0	0	B	A	2.	5	200					10.
MH 1-18	Ampl-Oscill.	D	1	5	0	0	3	0	2	B	A	10.	3	250	100					4.
		D	1	0	5	2	0	0	0	B	A		0	200						0.4
MH 4-100	Oscill-Oscill.	D	1	5	0	0	3	0	2	B	A	4.	-1.5	250	70					0.8
		D	1	0	5	2	0	0	0	B	A		0	100						0.4
M 0 4-65	Ampl Ocxill	D	1	5	0	0	3	0	2	B	A	4.	-1.5	250	70					1.8
		D	1	0	5	2	0	0	0	B	A	4.	0	100						0.5
P 1-90		G	5	0	2	0	0	0	0	0	B	A	1.5	15	160					18.
P 2-15		G	5	0	2	0	0	0	0	0	B	A	2.	16	160					15.
P 2-20		G	5	0	2	0	0	0	0	0	B	A	2.	16	160					14.
P 4-10	B h 08	G	5	0	2	0	0	0	0	0	B	A	4.	12	160					8.
P 4-14	B h 05	G	5	0	2	0	0	0	0	0	B	A	4.	16	100					14.
P 4-15		G	5	0	2	0	0	0	0	0	B	A	4.	25	160					14.
P 4-30		G	5	0	2	0	0	0	0	0	B	A	4.	30	200					25.
P 4-55		G	5	0	2	0	0	0	0	0	B	A	4.	15	230					30.
P 4-60		G	5	0	2	0	0	0	0	0	B	A	4.	30	200					25.
P 6-15		G	5	0	2	0	0	0	0	0	B	A	6.3	12	200					10.
P 20-18		G	5	1	2	0	0	0	0	0	B	A	20.	18	200					20.
P 4-100		G	5	3	2	0	0	0	0	0	B	A	4.	40	250	160				30.
PP 2-20		G	5	3	2	0	3	0	0	0	B	A	2.	5	200	160				6.
PP 2-22		G	5	3	2	0	3	0	0	0	B	A	2.	4	100	100				13.
PP 2-30		G	5	3	2	0	3	0	0	0	B	A	2.	16	200	160				12.
PP 4-15	B h 03	G	5	3	2	0	3	0	0	0	B	A	4.	12	200	100				12.
PP 4-15		G	5	3	2	0	3	0	0	0	B	A		12	200	70				10.
PP 4-30	C h 03	G	5	3	2	0	3	0	0	0	B	A	4.	16	160	160				20.
PP 4-3-1		G	5	3	2	0	3	0	0	0	B	A	4.	38	250	160				20.
PP 6-10		G	5	3	2	0	3	0	0	0	B	A	6.3	12	200	160				12.
PP 20-18		G	5	1	2	3	3	0	0	0	B	A	20.	22	200	200				25.
PP 40-18		G	5	1	2	3	3	0	0	0	B	A	40.	15	160	100				30.
PP 4-101	E h 03 H	G	5	3	2	0	3	0	0	0	B	A	4.	14	250	250				36.
PV 4-30	Plaque 1	G	6	0	0	0	0	0	0	0	B	A	4.		230					50.
	Plaque 2	G	0	0	6	0	0	0	0	0	B	A			250					50.

TYPE	MESURE	SOCLE	SELECTEUR									FILAM	GRILLE	PLAQUE	ECRAN I	ECRAN II	CATH	VIDE	DEBIT
			I	II	III	IV	V	VI	VII	VIII	IX								
506 PV475	Plaque 1	G	6	0	0	0	0	0	0	B	A	4.		250					50.
	Plaque 2		0	0	6	0	0	0	0	B	A			250					50.
PV495 PV30-18	Voir PV475 PL1	D	1	6	0	0	0	0	0	B	A	30.		250					50.
	PL2		0	0	0	0	6	1	0	B	A			250					50.
PV40-18	PL1	G	6	0	0	0	0	0	0	B	A	40.		250					50.
	PL2		0	0	6	0	0	0	0	B	A			250					50.
PV 4100	Voir PV475																		
PV4200	Voir PV475																		
PV4201	Voir PV475																		
R 150		G	5	0	2	0	0	0	0	B	A	1.1	0	200					40.
R 208		G	5	0	2	0	0	0	0	B	A	2.	3	200					1.
R 20-18		G	5	1	2	0	0	0	0	B	A	20.	3	200					4.
S 2-10		G	3	0	2	0	0	0	5	B	A	2.	3	200	100				2.
S 406		G	3	0	2	0	0	0	5	B	A	4.	3	200	100				4.
S 407		G	3	0	2	0	0	0	5	B	A	4.	3	200	100				1.8
S 410	Buy?	G	3	0	2	0	0	0	5	B	A	4.	3	200	100				4.
S 2018		G	3	1	2	0	0	0	5	B	A	20.	3	200	100				5.
SE 2018		G	3	1	2	0	0	0	5	B	A	20.	2	200	70				4.
SE 2118		G	3	1	2	0	0	0	5	B	A	20.	1.5	200	100				3.
SH4105	Ampl - Oscill -	D	1	5	3	0	0	0	2	B	A	4.		200					1.8
			1	0	0	4	2	0	0	B	A								0.5
SP 220		G	5	0	2	0	0	0	0	B	A	2.	1.5	160					15.
SP 230		G	5	0	2	0	0	0	0	B	A	2.	18.	160					16.
SP 614		G	5	0	2	0	0	0	0	B	A	6.3	14	200					18.
SS 20-18		G	5	0	2	0	0	0	0	B	A	20.	2	200	100				3.
V 431		G	6	0	6	0	0	0	0	B	A	4.		250					50.
V 475	Voir V 430																		
V 495	Voir V 430																		
V 2018		G	6	1	6	0	0	0	0	B	A	20.		250					50.
V 4200	Voir V 430																		

		SERIE HARMONIQUE																	
		B	0	6	0	0	0	0	0	0	B	A	4.		250				50.
AZ 11	PL 1	B	0	6	0	0	0	0	0	0	B	A	4.		250				50.
	PL 2	B	0	0	6	0	0	0	0	0	B	A	4.		250				50.
AZ 12	Voir AZ 11																		
EB 11	Diode 1	B	0	8	0	0	1	0	0	0	B	A	6.3		200				0.8
	Diode 2		0	0	8	1	0	0	0	0	B	A	6.3		200				0.8
EBC 11	Diode 1	B	1	1	5	2	1	0	0	0	B	A	6.3	8	250				5.
	Diode 2		8	0	0	0	1	0	0	0	B	A			200				0.8
EBF 11	Diode 1	B	0	8	0	0	1	0	0	0	B	A	6.3	2	200				0.8
	Diode 2		1	1	5	2	1	5	0	0	B	A	6.3	2	250	100			5.
ECH 11	Diode 1	B	0	0	0	0	1	0	0	0	B	A	6.3		200				0.8
	Diode 2		0	8	0	0	1	0	0	0	B	A			200				0.8
EDD 11	Triode 1	B	1	1	3	2	1	5	0	0	B	A	6.3	2	250	100			5.
	Triode 2		2	5	0	0	1	0	0	0	B	A	6.3	2	100				4.3
EF 11	Triode 1	B	2	5	0	0	1	0	0	0	B	A	6.3	6.3	250				3.5
	Triode 2		0	0	5	2	1	0	0	0	B	A		6.3	250				3.5
EF 12		B	0	5	3	2	1	0	0	0	B	A	6.3	2.	250	100			6.
EF 13		B	0	5	3	2	1	0	0	0	B	A	6.3	2.	250	250			3.
EPM 11	Pent h - Indic. Vis	B	1	5	3	2	1	0	0	0	B	A	6.3	1.5	250	100			4.5
			0	8	3	2	1	0	0	0	B	A	6.3	1.5	250				2.2
EL 11		B	0	8	5	2	1	3	0	0	B	A		0.25	250	250			VISUEL
			0	8	5	2	1	3	0	0	B	A	6.3	6	250	250			36.
EL 12		B	0	5	3	2	1	0	0	0	B	A	6.3	10	250	250			45.
EZ 11	PL 1	B	0	6	0	1	0	0	0	0	B	A	6.3		250				50.
	PL 2	B	0	0	6	1	0	0	0	0	B	A	6.3		250				50

LAMPES TRANSCONTINENTALES

TYPE	MESURE	SOCLE	SELECTEUR									FILAM	GRILLE	PLAQUE	ECRAN I	ECRAN II	CATH	VIDE	DEBIT
			I	II	III	IV	V	VI	VII	VIII	IX								
AB2	Diode 1	F	8	0	1	0	0	0	0	0	B	A	4.	250					1.
	Diode 2		0	8	1	0	0	0	0	B	A		250						1.
ABC1	Triode	E	5	0	0	0	1	0	2	B	A	4.	7	250					4.
	Diode 1		0	0	8	0	1	0	0	B	A			250					1.
	Diode 2		0	0	1	8	1	0	0	B	A			250					1.
ABL1	Penth-	E	5	3	0	0	1	0	2	B	A	4.	6	250	250				36.
	Diode 1		0	0	8	0	1	0	0	B	A			250					1.
	Diode 2		0	0	0	8	1	0	0	B	A			250					1.
AC2		E	5	0	0	0	1	1	2	B	A	4.	5.5	250					6.
AGH1	Penth-	E	5	3	1	1	1	1	2	B	A	4.	2	250	70				5.
	Triode	E	0	0	2	5	1	1	0	B	A		5	100					5.6
AD1		E	5	3	0	2	0	0	0	B	A	4.	4.5	250					60.
AF3		E	5	3	0	1	1	0	2	B	A	4.	3	250	100				8.
AF7		E	5	3	0	1	1	0	2	B	A	4.	2	250	100				3.
AK2	Ampl-	E	5	3	1	1	1	1	2	B	A	4.	3.5	250	70				4.
	Oscill-		0	0	2	5	1	1	2	B	A		0.5	250					1.
AL1		E	5	3	2	0	0	0	0	B	A	4.	15	250	250				36.
AL2		E	5	3	0	0	1	0	2	B	A	4.	25	250	250				36.
AL3		E	5	3	2	0	1	0	0	B	A	4.	6.5	250	250				36.
AL4		E	5	3	2	0	1	0	0	B	A	4.	6	250	250				36.
AL5		E	5	3	2	0	1	0	0	B	A	4.	16	250	250				72.
AM1		E	9	3	2	0	1	0	0	B	A	4.	0.5	250	250				VISUEL
AZ1	P.L.1	E	6	0	0	0	0	0	0	B	A	4.		250					50.
	P.L.2	E	0	0	0	6	0	0	0	B	A			250					50.
AZ4	Voir AZ1	E										4.							
AM2	Triode	E	5	0	2	0	1	0	0	B	A	4.	3.6	250					3.6
	Indic. C	E	9	3	0	2	1	0	0	B	A		0.2	250					VISUEL
CB1	Diode 1	F	0	8	1	0	0	0	0	B	A	13.		250					1.
	Diode 2	F	0	0	1	0	0	0	8	B	A			250					1.
CB2	Diode 1	F	8	0	1	0	0	0	0	B	A	13.		250					1.
	Diode 2	F	0	8	1	0	0	0	0	B	A			250					1.
CBC1	Triode	E	5	0	0	0	1	0	2	B	A	13.	5	200					4.
	Diode 1	E	0	0	8	0	1	0	0	B	A			250					1.
	Diode 2	E	0	0	0	8	1	0	0	B	A			250					1.
CBL1	Penth-	E	5	3	0	0	1	0	2	B	A	40.	8.5	200	200				45.
	Diode 1	E	0	0	8	0	1	0	0	B	A			250					1.
	Diode 2	E	0	0	0	8	1	0	0	B	A			250					1.
CC2		E	5	0	0	0	1	0	2	B	A	13.	5.5	250					6.
CF2		E	5	3	0	1	1	0	2	B	A	13.	2	200	100				4.5
CF3		E	5	3	0	1	1	0	2	B	A	13.	3	200	100				8
CF7		E	5	3	0	1	1	0	2	B	A	13.	2	250	100				5
CK1	Ampl-	E	5	3	0	0	1	0	2	B	A	13.	1.5	200	90				1.6
	Oscill-	E	0	0	2	5	1	0	0	B	A		0	200					1.4
CH1		E	5	3	1	2	1	0	2	B	A	13.	2	200	100				2.2
CL1		E	5	3	0	0	1	0	2	B	A	13.	14	200	200				25.
CL2		E	5	3	0	0	1	0	2	B	A	24.	19	200	100				40.
CL4		E	5	3	0	0	1	0	2	B	A	35.	8.5	200	200				45.

TYPE	MESURE	SOCLE	SELECTEUR									FILAM.	GRILLE	PLAQUE	ECRAN I	ECRAN II	CATH.	VIDE	DEBIT
			J	II	III	IV	V	VI	VII	VIII	IX								
CL6		F	5	3	0	0	-1	0	2	B	A	35.	9.5	200	-100			45.	
CY1		F	6	0	0	0	0	-1	0	B	A	20.		250				50.	
CY2	PL1	F	6	0	0	0	0	-1	0	B	A	30.		250				50.	
	PL2	F	0	0	0	6	-1	0	0	B	A	30.		250				50.	
CK3	Ampl.	F	5	3	0	0	0	-1	0	2	B	A	20.	2.5	200	100		2.5	
	Oscill.	F	0	0	2	5	-1	0	0	B	A	20.	0	120				3.	
EB1	Diode 1	F	0	0	8	-1	0	0	0	B	A	6.3		250				1.	
	Diode 2	F	0	0	0	4	0	0	0	B	A			250				1.	
EAB1	Diode 1	F	0	0	8	0	0	-1	0	0	B	A	6.3		250			1.	
	Diode 2	F	0	0	8	0	0	-1	0	0	B	A			250			1.	
	Diode 3	F	0	0	0	8	-1	0	0	B	A			250				1.	
EBC3	Diode 1	E	5	0	0	0	0	-1	0	2	B	A	6.3	5.5	250			5.	
	Diode 2	E	0	0	0	8	0	-1	0	0	B	A			250			1.	
	Diode 2	E	0	0	0	-1	8	-1	0	0	B	A			250			1.	
EBF1	Pentb.	F	5	3	0	0	-1	0	2	B	A	6.3	3	250	-125			9.	
	Diode 1	F	0	0	0	8	0	-1	0	0	B	A			250			1.	
	Diode 2	F	0	0	0	8	-1	0	0	B	A			250				1.	
EBF2	Pentb.	E	5	3	0	0	-1	0	2	B	A	6.3	2	250	100			5.	
	Diode 1	E	0	0	0	8	0	-1	0	0	B	A			250			1.	
	Diode 2	E	0	0	0	8	-1	0	0	B	A			250				1.	
EBL1	Pentb.	E	5	3	0	0	-1	0	2	B	A	6.3	6	250	250			36.	
	Diode 1	E	0	0	0	8	0	-1	0	0	B	A			250			1.	
	Diode 2	E	0	0	0	8	-1	0	0	B	A			250				1.	
EC2		E	5	0	0	0	-1	0	2	B	A	6.3	5.5	250				6.	
ECH3	Ampl.	E	5	3	-1	-1	-1	-2	B	A	6.3	3	250	-100				4.	
	Oscill.	E	0	0	2	5	-1	-1	0	B	A		5	-140				6.	
EE1	dur C.Ch.	E	0	3	0	5	-1	0	2	B	A	6.3	3.6	160	-160			5.5	
	dur C.Fe.	E	5	3	0	3	-1	0	2	B	A		3.6	250	160			6.	
EFM1	Pentb.	E	5	3	2	6	-1	0	0	B	A	6.3	2	250	100			3.	
EF1		E	5	3	0	-1	-1	0	2	B	A	6.3	2	250	100			3.	
EF2		E	5	3	0	-1	-1	0	2	B	A	6.3	2	250	100			4.5	
EF5		E	5	3	0	-1	-1	-2	B	A	6.3	3	250	100				8.	
EF6		E	5	3	0	-1	-1	-2	B	A	6.3	2	250	100				3.	
EF8		E	5	3	-1	-1	-1	-2	B	A	6.3	2.5	250	250				8.	
EF9		E	5	3	-1	0	-1	0	2	B	A	6.3	2.5	250	100				6.
EH2		E	5	3	4	2	-1	0	2	B	A	6.3	3	250	100	100			4.2
EK2	Ampl.	F	5	3	-1	-1	-1	0	-1	B	A	6.3	2	250	70				4.
	Oscill.	F	0	0	2	5	-1	0	1	B	A		0.4	250				1.	
EK3	Ampl.	E	5	3	-1	0	-1	0	2	B	A	6.3	3	250	-100				7.
	Oscill.	E	0	0	2	5	-1	0	0	B	A		5	135				4.	
ELL1	Pentb. 1	F	5	3	0	0	-1	2	0	B	A	6.3	21.5	250	250				14.5
	Pentb. 2	F	0	3	2	5	-1	0	0	B	A		21.5	250	250				14.5
EL1		F	5	3	0	0	-1	0	2	B	A	6.3	19	250	250				32.
EL2		F	5	3	0	0	-1	0	2	B	A	6.3	20	250	250				30.
EL3		F	5	3	2	0	-1	0	0	B	A	6.3	6	250	250				36.
EL5		F	5	3	2	0	-1	0	0	B	A	6.3	16	250	250				72.
EL6		F	5	3	2	0	-1	0	0	B	A	6.3	8	250	250				72.
EM1-		F	9	3	2	0	-1	0	0	B	A	6.3	0-8	250	250				VISUEL
EM3		F	9	3	2	0	-1	0	0	B	A	6.3	0-8	250	250				VISUEL
EM4		F	9	3	2	-1	-1	0	0	B	A	6.3	0-5	250	250				VISUEL
	Gr. dens.	F	-1	3	2	9	-1	0	0	B	A	6.3	0-9	250	250				VISUEL
EZ1	PL 1	E	6	0	0	0	-1	0	0	B	A	6.3		250					50.
	PL 2	E	0	0	0	6	-1	0	0	B	A			250					50.

ARTEX

NOUVELLES LAMPES

ANALYSEUR
LABORATOIRE

U60

TYPE	MESURE	SOCLE	SELECTEUR									FILAM	GRILLE	PLAQUE	ECRAN I.	ECRAN II.	CATH.	VIDE	DEBIT	
			I	II	III	IV	V	VI	VII	VIII	IX									
DAF 11	PENTHODE DIODE	B	0	0	3	2	0	5	0	B	A	4,1	0	120	20	.	.	.	0,3	
		B	0	8	1	1	0	1	0	B	A	4,1	0	250	1	
DE 11	TRIODE	B	0	5	0	2	0	0	0	B	A	1,1	4,5	120	2,5	
		B	0	0	3	2	0	5	0	B	A	1,1	0	120	60	.	.	.	1	
DCH 11	HEXODE TRIODE	B	2	5	0	0	0	0	0	B	A	1,1	3	80	1,2	
		B	2	5	0	0	0	0	0	B	A	1,1	4,5	120	1,5	
DD 11	TRIODE I TRIODE II	B	0	0	5	2	0	0	0	B	A	1,1	4,5	120	1,5	
		B	0	5	3	2	0	0	0	B	A	1,1	0	120	60	.	.	.	1,2	
DF 11	PENTHODE	B	0	5	3	2	0	0	0	B	A	1,1	0	120	60	.	.	.	1,2	
		B	0	5	3	2	0	0	0	B	A	1,1	6	120	120	.	.	.	4,7	
BB 1	DIODE I DIODE II	G	8	1	1	0	0	0	0	B	A	16	.	250	1	
		G	0	1	1	0	0	0	8	B	A	16	.	250	1	
BCH 1	HEXODE TRIODE	D	1	5	1	1	3	0	2	B	A	25	2	200	50	.	.	.	1,3	
		D	1	1	2	5	1	0	1	B	A	25	5	200	4	
BL 2	PENTHODE	G	5	1	3	0	0	0	2	B	A	30	20	200	100	.	.	.	40	
		E	5	1	1	3	1	1	2	B	A	20	2	200	50	.	.	.	2	
CC 1	HEXODE TRIODE	E	1	2	5	1	1	1	1	B	A	20	5	200	4	
		E	5	3	4	2	1	1	2	B	A	6,3	2	250	80	80	.	.	.	3
EH 1	HEXODE	E	5	3	1	4	1	1	2	B	A	6,3	1,5	250	70	90	.	.	.	1,6
ECL 11	PENTHODE TRIODE	B	3	2	1	1	1	5	0	B	A	6,3	6	250	250	.	.	.	36	
		B	1	1	5	2	1	1	0	B	A	6,3	2	200	2,5	
EF 11	PENTHODE	B	1	5	2	1	1	3	0	B	A	6,3	4,5	200	200	.	.	.	12	
		B	0	9	9	2	1	5	0	B	A	6,3	VAR.	250	VISUEL	
JBF 11	PENTHODE DIODE I DIODE II	B	1	1	3	2	1	5	0	B	A	20	2	200	80	.	.	.	5	
		B	1	1	1	1	1	1	0	B	A	20	1	
UCH 11	HEXODE TRIODE	B	1	1	3	2	1	5	0	B	A	20	2	200	80	.	.	.	2,5	
		B	2	5	1	1	1	1	0	B	A	20	5	200	4	
VCL 11	PENTHODE TRIODE	B	3	2	1	1	1	5	0	B	A	60	8,5	200	200	.	.	.	45	
		B	1	1	5	2	1	1	0	B	A	60	2	200	2	
VDF 11	VALVE	B	0	6	0	1	0	0	0	B	A	50	50	
		E	5	3	1	2	1	1	2	B	A	6,3	2	250	100	.	.	.	2,5	
VCH 4	HEXODE TRIODE	E	1	1	2	1	5	1	1	B	A	6,3	5	200	4	
		E	5	3	1	1	1	1	2	B	A	40	9	100	100	.	.	.	45	
CBL 6	PENTHODE DIODE I DIODE II	E	1	1	1	1	1	1	1	B	A	40	.	250	1	
		E	1	1	1	1	1	1	1	B	A	40	.	250	1	